

## Hexagon | NovAtel Support

# Firmware Update Instructions

### NOTE:

This folder contains the MarinePak7 firmware package version 1.4.0.

The Firmware package 1.4.0. can be loaded on all MarinePak7 receivers

Before starting the upgrade, please record all configuration details and download any logged project data files as these will be lost during the update process.

### Update Procedure:



1. Copy the update file MarinePak7\_1.4.0.mrx to the root folder of a USB memory drive.
2. Power up the MarinePak7 and allow the system to fully boot.
3. Ensure the screen saver is deactivated by pressing any of the front panel buttons and insert the USB memory drive into the front panel USB port (highlighted above).
4. Wait a few seconds for the MarinePak7 to detect the update file on the USB memory drive. When the file is detected a message will be displayed:-



5. The displayed filename should match the update file. Press the centre tick button to start the update.
6. The update will take approximately five minutes to complete. The MarinePak7 will be reset to factory default settings and will be rebooted twice.
7. After the final reboot the MarinePak7 will display the POSTION STATUS screen. The update is now complete, and the USB memory drive can be removed.

If you have any questions or concerns regarding this update process, more information can be found on our [support pages](#).

## Contact Hexagon | NovAtel

support.novatel@hexagon.com 1-800-NOVATEL (U.S. and Canada) or 1-403-295-4900  
For more contact information, please visit [novatel.com/contact-us](http://novatel.com/contact-us)